

Product Name: SECURE S

General information

- This luminaire must be installed in accordance with the latest edition of the IET Wiring Regulations and local Building Regulation by a qualified competent person.
- The mains power supply must be turned off before inspection, installation or removal of the luminaire, ensuring that the supply is locked off to prevent inadvertently switching the supply on.
- It is the installer's responsibility to ensure that the installation is suitable for the total load of the luminaire(s). The supply cable fuses/circuit breakers must be correctly rated for the electrical load and taking into account for any transient inrush currents that may occur.
- It is the installer's responsibility to ensure that the environmental operating and storage conditions are complied with and that any fire risks are considered.
- Do not perform insulation strength or insulation resistance tests on the installation with the luminaire(s) connected, this can damage the luminaires and give erroneous readings.
- Do not loop-in supply cables at the luminaire supply terminals unless there is provision for 2-way connection at the terminals.
- The light source contained in this luminaire must only be replaced by TamLite Lighting or an appointed service agent.
- Emergency lighting luminaires must be installed and maintained in accordance with the emergency lighting standard BS 5266-1.
- To ensure that the product warranty remains valid, the luminaire must be installed and maintained in accordance with these installation instructions and the product must not be modified in any way.



Luminaires marked with this symbol must not be covered with thermally insulating material.



This symbol on covers over light sources indicates dangerous live parts do not operate the luminaire with this cover removed.

Dimensions

Note: The luminaire is mounted with Security Torx screws. Security Torx tool is required.

	A (mm)	B (mm)	C (mm)	Fixing Points (mm)
SCS4300 / SCS4400	1250	175	85	1100x80
SCS5330 / SCS5400 / SCS5500	1525	175	85	1375x80

Product Name: **SECURE S**

<p>1</p> <p>Remove the product from its packaging.</p>	<p>2</p> <p>Remove all tamper proof screws and diffuser.</p>
<p>3</p> <p>Remove tamper proof screws and LED gear tray.</p>	<p>4</p> <p>Prepare appropriate holes on the mounting surface.</p>
<p>5</p> <p>Feed the mains cable through the grommet and secure luminaire body to surface.</p>	<p>6</p> <p>Terminations shown for standard, emergency and DALI variants.</p>
<p>7</p> <p>Reattach the LED gear tray, diffuser and trim.</p>	<p>8</p> <p>Apply Anti-Pick Mastic (not supplied) all around the edge of the luminaire.</p>

Page 2 of 2

Tamlite Technical
 Stafford Park 12,
 Telford, Shropshire,
 TF3 3BJ

+44(0)1952 292441
 technical@tamlite.co.uk
 Document No: V1

			220-240V 50/60Hz		IP65	IK15 125 Joules	ta 0°C to 25°C 5°C to 25°C for M3 variants
--	--	--	---------------------	--	------	--------------------	---